

Control Panels | FEATURE CHART

LYNX Plus (L3000) VISTA-10P VISTA-15P VISTA-20P VISTA-21iP VISTA-50P

| | LYNX Plus (L3000) | VISTA-10P | VISTA-15P | VISTA-20P | VISTA-21iP | VISTA-50P |
|--|-------------------|-----------|-----------|-----------|------------|-------------|
| System Capacities | | | | | | |
| Max. Zone Capacity | 41 | 22 | 32 | 48 | 48 | 86 |
| Std. Hardwired Zones (w/zone doubling) | 1 | 6 (-) | 6 (-) | 8 (15) | 8 (15) | 9 (-) |
| Max. ECP Hardwire Expansion Zones | N/A | 0 | 16 | 40 | 40 | N/A |
| Max. V-Plex Expansion Zones | N/A | N/A | N/A | N/A | N/A | 77 |
| Max. Wireless Expansion Zones | 24 | 16 | 26 | 40 | 40 | 85 |
| Wireless Keys (do not use zones) | 16 | 8 | 8 | 16 | 16 | 0 |
| Partitions | N/A | 1 | 1 | 2 "true" | 2 "true" | 8 |
| User Codes | 8 | 16 | 32 | 48 | 48 | 75 |
| Event Log | 84 | 32 | 50 | 100 | 100 | 224 |
| Max. No. Two-Wire Smokes | N/A | 0 | 16 | 16 | 16 | 16 |
| Max. Number of Schedules | 8 | 2 | 8 | 32 | 32 | 20 |
| False Alarm Prevention Features | | | | | | |
| Exit Error Logic | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Exit Delay Reset | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Exit Delay Countdown | ✓ | ✓ | ✓ | ✓ | ✓ | - |
| Cross Zoning | N/A | ✓ | ✓ | ✓ | ✓ | ✓ |
| Alarm Verification - Fire | ✓ (SIA) | ✓ | ✓ | ✓ | ✓ | - |
| Swinger Shutdown | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Unvacated Auto-Stay | N/A | ✓ | ✓ | ✓ | ✓ | - |
| Alarm Cancel Verification | ✓ (SIA) | ✓ | ✓ | ✓ | ✓ | - |
| System Configuration | | | | | | |
| Interactive Phone Support | ✓ (Built-in) | ✓ | ✓ | ✓ | ✓ | ✓ |
| Real Time Clock | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Temporal Bell | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Bell Supervision | - | ✓ | ✓ | ✓ | ✓ | ✓ |
| Telephone Line Monitor | - | - | ✓ | ✓ | ✓ | - |
| On-Board Triggers | - | 2 | 2 | 2 | 2 | 4 |
| Relays Supported | N/A | 4 | 8 | 16 | 16 | 16 |
| X-10 Devices Supported | 8 | - | 8 | 16 | 16 | 16 |
| Integrated Internet | N/A | N/A | N/A | N/A | ✓ | N/A |
| Additional Features | | | | | | |
| Master Console | N/A | N/A | N/A | - | - | ✓ |
| Cross Partitioning (goto) | N/A | - | - | ✓ | ✓ | ✓ |
| "Night" Arming | ✓ | ✓ | ✓ | ✓ | ✓ | - |
| RF Supervision by Transmitter | N/A | ✓ | ✓ | ✓ | ✓ | ✓ |
| Common Lobby Logic | N/A | N/A | N/A | ✓ | ✓ | ✓ |
| Configurable Zone Type | - | ✓ | ✓ | ✓ | ✓ | - |
| "Battery Saver" | - | - | ✓ | ✓ | ✓ | - |
| Keyswitch Arming | N/A | ✓ | ✓ | ✓ | ✓ | ✓ |
| Convenience Features | | | | | | |
| Single Button Arming | ✓ | ✓ | ✓ | ✓ | ✓ | - |
| Quick Exit | ✓ | ✓ | ✓ | ✓ | ✓ | - |
| Keypad Macros | - | ✓ | ✓ | ✓ | ✓ | ✓ |
| Viewable Event Log at Keypad | - | ✓ | ✓ | ✓ | ✓ | ✓ |
| Time & Date Display | ✓ | - | - | - | - | - |
| Pager Capability | ✓ | 1 | 2 | 4 | 4 | - |
| Auto Arm/Disarm | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Graphic Keypad Support | 2 x 16 Alpha | - | 2 | 4 | 4 | - |
| Internet and GSM Communication Support | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ (Trigger) |

✓ (Supported Feature)

- (Not Supported)

N/A (Not Applicable)